


# RESOURCE GUIDE - POWER & CONTROL

## RGBW TOUCH PANEL | S3i





### WIRING DIAGRAM



### PAIRING

Turn on the Touch Panel (Indicator light will turn BLUE).  
Click the Learning Key on the NF-S3i-WR-1009  
Select your "ZONE" (# Z1-Z3) then play with color panel



Nova Flex LED, LLC. retains the right to modify the design of our products at any time as part of the company's continual product improvement program.

PROJECT

FIXTURE

PHASE

DATE

Rev: Oct.18.23/20:10

800.595.6302

novaflexled.com

# RESOURCE GUIDE - POWER & CONTROL

## RGBW TOUCH PANEL | S3I









### OPERATION




#### Zones – 3 Zone

Select color of preference. Press and hold “ZONE” number for 3 seconds (lights should flash when stored successfully).

#### Color Change


RGBW - Adjust Color Wheel 





RGB – To Select only SOLID colors, press  OR  OR  OR  surrounding the Color Wheel (ON/OFF functions, will have to press color (RED/GREEN/BLUE/WHITE) again to turn OFF after turning ON). (I.E. Selecting  and  simultaneously will provide YELLOW)

To change to solely WHITE, change to SOLID MODE by Selecting (1) of the SOLID colors on the Touch Panel (, , ). Once the Touch Panel is in SOLID MODE, turn OFF ALL SOLID colors by selecting each color until the light goes OUT. Once the light is

out, press the  surrounding the Color Wheel once to turn ON.

#### Brightness – RGB

Press and hold Sun  to adjust brightness (release button and press and hold again to go opposite direction).

When using MULTIPLE R/G/B/W SOLID colors, can adjust brightness by pressing and holding down each  OR  OR  OR  surrounding the Color Wheel. Press and hold to brighten each color (release and press and hold again to go opposite direction). Also works when mixing SOLID R/G/B/W colors!